

# Android™ Release Notes

## 1 Release Description

The i.MX Android™ P9.0.0\_1.0.0-ga release is an RFP (GA) release for the Android Pie 9.0 (P) on NXP's i.MX 8M Mini, i.MX 8M Quad, i.MX 8QuadMax, and i.MX 8QuadXPlus applications processors.

i.MX Android P9.0.0\_1.0.0-ga release includes all necessary code, documents, and tools to assist users in building and running the Android Pie 9.0 on the i.MX 8M Mini, i.MX 8M Quad, i.MX 8QuadMax, and i.MX 8QuadXPlus Board.

The prebuilt images are also included for a quick trial on NXP i.MX 8M Mini, i.MX 8M Quad, i.MX 8QuadMax, and i.MX 8QuadXPlus Board and Platforms.

This release includes all porting and enhancements based on the Android open source code.

Most of the deliveries in this release are provided in source code with the exception of some proprietary modules/libraries from third parties.

## 2 Supported Hardware SoC/Boards

The supported hardware system-on-chip (SoCs)/boards are listed as follows:

### Contents

1	Release Description.....	1
2	Supported Hardware SoC/Boards.....	1
3	Release Package Contents.....	2
4	Features .....	3
5	Multimedia Codecs.....	6
6	Extended Feature Packages.....	6
7	Change Logs.....	7
8	Known Issues and Limitations.....	7
9	Revision History.....	8



## Release Package Contents

- i.MX 8M Mini EVK Rev. B Board and Platform
- i.MX 8M Quad EVK Rev. B3/B4 Board and Platform
- i.MX 8QuadMax MEK Rev. B0 Board and Platform
- i.MX 8QuadXPlus MEK Rev. B0 Board and Platform

## 3 Release Package Contents

The P9.0.0\_1.0.0-ga release package includes the following software and documents.

**Table 1. Release package contents**

i.MX Android proprietary source code package	<ul style="list-style-type: none"><li>• imx-p9.0.0_1.0.0-ga.tar.gz: i.MX Android proprietary source code package to enable Android on i.MX boards. For example, Hardware Abstraction Layer implementation, hardware codec acceleration, etc.</li></ul>
Documents	<p>The following documents are included in android_p9.0.0_1.0.0-ga_docs.zip:</p> <ul style="list-style-type: none"><li>• <i>Android™ Quick Start Guide (AQSUG)</i>: A document that explains how to run the Android platform on an i.MX board using prebuilt images.</li><li>• <i>Android™ User's Guide (AUG)</i>: A document describing procedures for configuring and building this release package.</li><li>• <i>Android™ Release Notes (ARN)</i>: A document that introduces key updates and known issues in this release.</li><li>• <i>i.MX Android™ Extended Codec Release Notes (IMXACRN)</i>: A document that provides the extended codec information.</li><li>• <i>Android™ Frequently Asked Questions (AFAQ)</i>: A document that contains the answers to the Frequently Asked Questions (FAQs).</li><li>• <i>i.MX Graphics User's Guide (IMXGRAPHICUG)</i>: A document that describes GPU 2D API, Tools, Memory, and Application programming guidelines.</li></ul>
Tools	<p>Tools in android_p9.0.0_1.0.0-ga_tools.tar.gz</p> <ul style="list-style-type: none"><li>• VivanteVTK-6.2.4.p2.1.7.6.tgz: GPU tools for VeriSilicon GPU 6.2.4.p2 driver. For more information about these tools, see <i>i.MX Graphics User's Guide (IMXGRAPHICUG)</i>.</li><li>• fsl-sdcard-partition.sh: tool to make partition and flash Android images.</li><li>• fastboot_imx_flashall.sh: A script for Linux system. It invokes fastboot tool to automatically flash Android images.</li><li>• fastboot_imx_flashall.bat: A batch file for Windows system. It invokes fastboot tool to automatically flash Android images.</li><li>• uuu_imx_android_flash.sh: A script for Linux system. It invokes UUU and fastboot tool to automatically flash Android images.</li><li>• uuu_imx_android_flash.bat: A batch file for Windows system. It invokes UUU and fastboot tool to automatically flash Android images.</li></ul>
Prebuilt images	<p>You can test the Android platform with a prebuilt image on i.MX reference board before building any code:</p> <ul style="list-style-type: none"><li>• android_p9.0.0_1.0.0-ga_image_8mmevk.tar.gz: Prebuilt images with NXP extended features for the i.MX 8M Mini EVK board. The extended features include additional multimedia format support.</li><li>• android_p9.0.0_1.0.0-ga_image_8mqevk.tar.gz: Prebuilt images with NXP extended features for the i.MX 8M Quad EVK board. The extended features include more multimedia format support.</li><li>• android_p9.0.0_1.0.0-ga_image_8qmek.tar.gz: Prebuilt images with NXP extended features for the i.MX 8QuadMax/8QuadXPlus MEK board. The extended features include more multimedia format support.</li></ul> <p>All prebuilt images are in a separate package. See the <i>Android™ Quick Start Guide (AQSUG)</i> and <i>Android™ User's Guide (AUG)</i> to choose the appropriate image.</p>

## 4 Features

This section contains features in this package.

**Table 2. Features**

Feature	i.MX 8M Mini EVK	i.MX 8M Quad EVK	i.MX 8QuadMax MEK	i.MX 8QuadXPlus MEK	Remarks
Google Pie 9.0 release	Y	Y	Y	Y	Based on android-9.0.0_r16 release
Linux 4.14.78 kernel (merged with the AOSP kernel)	Y	Y	Y	Y	Based on Linux® OS BSP L4.14.78-1.0.0_ga release.
U-Boot	Y	Y	Y	Y	v2018.03.
Graphic-HW	Y	Y	Y	Y	VeriSilicon GC7000NanoUltr GPU with the 6.2.4.p2 driver for i.MX 8M Mini.  VeriSilicon GC7000L GPU with 6.2.4.p2 driver for i.MX 8M Quad.  VeriSilicon GC7000XSVX GPU with 6.2.4.p2 driver for i.MX 8QuadMax.  VeriSilicon GC7000L GPU with 6.2.4.p2 driver for i.MX 8QuadXPlus.
Graphic-HW 3D acceleration	Y	Y	Y	Y	OpenGL ES1.1/2.0 through GC7000NanoUltr for i.MX 8M Mini.  OpenGL ES1.1/2.0/3.1 through GC7000L for i.MX 8M Quad.  OpenGL ES 1.1/2.0/3.1/3.2 through GC7000XSVX for i.MX 8QuadMax.  OpenGL ES 1.1/2.0/3.1 via GC7000L for i.MX 8QuadXPlus.
Graphic-HW accelerated UI surface composition	Y	Y	Y	Y	OpenGL ES2.0 through GC7000NanoUltr for i.MX 8M Mini.  OpenGL ES3.1 through GC7000L for i.MX 8M Quad, OpenGL ES 3.2 through GC7000XSVX for i.MX 8QuadMax.  OpenGL ES 3.1 through GC7000L for i.MX 8QuadXPlus.
Boot source	SD/eMMC	SD/eMMC	SD/eMMC	SD/eMMC	-
Splash Screen	Y	Y	Y	Y	-
UI (input)	Y	Y	Y	Y	-
UI (display)	MIPI-to-HDMI/MIPI panel display	HDMI/MIPI-to-HDMI/MIPI panel display	HDMI display	HDMI display	i.MX 8M Mini supports MIPI-DSI to HDMI display and MIPI Panel display.

Table continues on the next page...

Table 2. Features (continued)

Feature	i.MX 8M Mini EVK	i.MX 8M Quad EVK	i.MX 8QuadMax MEK	i.MX 8QuadXPlus MEK	Remarks
					i.MX 8M Quad supports physical HDMI display, MIPI-DSI to HDMI display, and MIPI panel display. i.MX 8QuadMax supports LVDS-to-HDMI/MIPI-to-HDMI and physical HDMI display.
UI (dual display, HDMI+HDMI, UI mirror displayed on second device)	N	Y	Y	Y	Supports dual LVDS-to-HDMI display.
UI (brightness control)	N	N	N	N	-
Storage - External Media	Y	Y	Y	Y	USB 2.0 port supports udisk, but USB 3.0 port does not support udisk.
Connectivity - Ethernet	Y	Y	Y	Y	-
Connectivity - Bluetooth® wireless technology	Y	Y	Y	Y	Hardware: <ul style="list-style-type: none"> <li>Qualcomm 1PJ QCA9377 for i.MX 8M Mini</li> <li>Qualcomm 1CQ QCA6174A for i.MX 8M Quad, i.MX 8QuadMax, and i.MX 8QuadXPlus.</li> </ul> Profiles: <ul style="list-style-type: none"> <li>A2DP Source</li> <li>AVRCP</li> <li>BLE Host</li> <li>HSP</li> <li>HID Host</li> <li>HID Device</li> <li>PAN</li> <li>OPP</li> </ul>
Connectivity - Wi-Fi	Y	Y	Y	Y	Hardware: <ul style="list-style-type: none"> <li>Qualcomm 1PJ QCA9377 for i.MX 8M Mini</li> <li>Qualcomm 1CQ QCA6174A for i.MX 8M Quad, i.MX 8QuadMax, and i.MX 8QuadXPlus</li> </ul> Features: <ul style="list-style-type: none"> <li>STA mode</li> <li>AP mode</li> <li>Wi-Fi Direct</li> <li>AP/STA Concurrency</li> </ul>
Connectivity - USB Tethering	Y	Y	Y	Y	Supports Wi-Fi and Ethernet as upstream.
Power - CPU Freq	Y	Y	Y	Y	-

Table continues on the next page...

Table 2. Features (continued)

Feature	i.MX 8M Mini EVK	i.MX 8M Quad EVK	i.MX 8QuadMax MEK	i.MX 8QuadXPlus MEK	Remarks
Power - Bus Freq	Y	Y	Y	Y	-
Media - Music Play	Y	Y	Y	Y	SSI + WM8524 for i.MX 8M Mini and i.MX 8M Quad. ESAI+CS42888 for i.MX 8QuadMax (not support multichannel). ESAI+CS42888 for i.MX 8QuadXPlus (supports multichannel).
Media-Sound Record	Y	Y	Y	Y	-
Media - Video Play	Y	Y	Y	Y	-
Media - Camera	Y	Y	Y	Y	OV5640CSI for i.MX 8M Mini and i.MX 8M Quad. OV5640MIPI for i.MX 8QuadXPlus. For i.MX 8M Quad, the camera cannot co-work with MIPI Display due to the I2C address conflict.
Media - TVIN	N	N	N	N	-
Media - Dual Camera	Y	Y	Y	Y	Dual OV5640MIPI for i.MX 8QuadMax OV5640MIPI and OV5640CSI for i.MX 8QuadXPlus
Media - Camcorder	Y	Y	Y	Y	-
Media - USB Camera	Y	Y	N	N	USB camera supports C920, C270, and C525.
Media - USB Mic	Y	Y	Y	Y	-
Media - HDMI audio output	N	Y	N	N	-
Media-DSD Playback	Y	Y	N	N	DSD stream output from Audio Expansion Board.
Media-PlayReady DRM	N	Y	N	N	Moderated download for licensees
Media-WideVine DRM	N	Y	N	N	Moderated download for licensees
Media-M4 Playback	Y	N	N	N	Audio playback based on FreeRTOS on the Cortex-M4 core for i.MX 8M Mini.
Media-Hi-Res audio output	Y	N	N	N	High resolution audio output from Audio Expansion Board for i.MX 8M Mini. <ul style="list-style-type: none"> <li>2 channel: 384000, 768000 sampling rate</li> <li>4 channel: 48000, 96000, 192000, 384000, 768000 sampling rate</li> </ul>

Table continues on the next page...

Table 2. Features (continued)

Feature	i.MX 8M Mini EVK	i.MX 8M Quad EVK	i.MX 8QuadMax MEK	i.MX 8QuadXPlus MEK	Remarks
					<ul style="list-style-type: none"> <li>6 channel: 48000, 96000, 192000, 384000 sampling rate</li> <li>8 channel: 48000, 96000, 192000, 384000 sampling rate</li> </ul>
Misc - ADB over USB	Y	Y	Y	Y	-
Misc - Fastboot utility	Y	Y	Y	Y	-
Misc - SW update and factory reset	Y	Y	Y	Y	-
Sensor - Magnetometer	N	N	Y	Y	FXOS8700
Sensor - Accelerometer	N	N	Y	Y	FXOS8700
Sensor - Gyroscope	N	N	Y	Y	FXAS2100
Sensor - Light	N	N	Y	Y	ISL29023
Sensor - Pressure	N	N	Y	Y	MPL3115
Sensor - Temperature	N	N	Y	Y	MPL3115
File Based Encryption	N	N	Y	Y	-
USB Accessory	Y	Y	Y	Y	Google AOA v2.0
Ethernet APK	Y	Y	Y	Y	-
webGL	Y	Y	Y	Y	-
Vulkan	N	Y	Y	Y	-
OTA for A/B	Y	Y	Y	Y	-
USB Type-C PD	Y	Y	Y	Y	Supports power role switch with devices that support USB power delivery
DM Verity	Y	Y	Y	Y	-

## 5 Multimedia Codecs

For multimedia codecs and features, see Section 5 in the [Google Pie 9.0 Compatibility Definition Document \(CDD\)](#).

## 6 Extended Feature Packages

An enhanced multimedia experience is available for the Android platform. This release delivers an error-resilient, feature-rich multimedia solution by extending the existing multimedia features of the Android platform and introduces additional features.

For more information about the features below, contact "L2manager-android@nxp.com". For detailed extended and additional features, see *i.MX Android™ Extended Codec Release Notes (IMXACRN)*.

## 7 Change Logs

Compared to the P9.0.0\_1.0.0-beta release, this release has the following major changes:

- Upgraded the Android code base from android-9.0.0\_r8 to android-9.0.0\_r16.
- Upgraded the kernel from 4.14.62 to 4.14.78.
- Enabled VNDK full build system support.

## 8 Known Issues and Limitations

The known issues about the hardware and hardware rework instructions are not included in this document. There may be hardware-related reference materials for some reference boards. Make sure to check the link [i.MX Application Processors](#) to see if it is applicable.

**Table 3. Known issues and limitations**

Issue description	Remarks
The Google USB driver must be installed multiple times for the MTP, PTP, MTP&ADB, PTP&ADB, and ADB function settings.	Some Windows XP environments may display MTP and PTP windows even with only PTP enabled in the device.
U-Boot will hang when erasing Kingston SD card.	U-Boot will hang when sending the erase command on some Kingston SD cards.
The display is sometimes black on both the i.MX 8QuadMax MEK and i.MX 8QuadXPlus MEK boards.	<ul style="list-style-type: none"> <li>• The display is sometime black without any abnormal log or with the following log on both the i.MX 8QuadMax and i.MX 8QuadXPlus MEK board.</li> </ul> <pre>imx-dpu-crtc imx-dpu-crtc.4: flush - wait for content shld done timeout.</pre> <ul style="list-style-type: none"> <li>• It is caused by the hardware PMIC issue on both the i.MX 8QuadMax and i.MX 8QuadXPlus board.</li> <li>• The workaround is as follows: Disable selinux and switch to root user by su.</li> </ul> <pre>echo performance &gt; /sys/devices/system/cpu/cpufreq/policy4/scaling_governor.</pre>
The resolution of the screen recorded video is different from the one specified by the recording command, and the color of the video is different from the screen color.	Android platform needs RGBA format output, but the V4L2 framework does not support this format. To support RGBA format output in the mem2mem driver, the V4L2 format needs to be extended.
For i.MX 8QuadXPlus, it fails to boot from some types of eMMC.	<p>In the default settings, the UUU script burns the boot image into eMMC Boot Partition with 32KB offset. Although it works properly on the MEK board, it fails to read the boot image on some types of eMMC.</p> <p>There are two possible solutions:</p> <ul style="list-style-type: none"> <li>• Download flash.bin in the eMMC Boot Partition + 0KB offset + eMMC fastboot enabled in fuse.</li> <li>• Download flash.bin in the eMMC User Partition + 32KB offset (eMMC fastboot can be either enabled or disabled in fuse).</li> </ul> <p>For more information, see <a href="https://community.nxp.com/docs/DOC-342285">https://community.nxp.com/docs/DOC-342285</a>.</p>

## 9 Revision History

**Table 4. Revision history**

Revision number	Date	Substantive changes
P9.0.0_1.0.0-beta	11/2018	Initial release
P9.0.0_1.0.0-ga	01/2019	



**How to Reach Us:****Home Page:**[nxp.com](http://nxp.com)**Web Support:**[nxp.com/support](http://nxp.com/support)

Information in this document is provided solely to enable system and software implementers to use NXP products. There are no express or implied copyright licenses granted hereunder to design or fabricate any integrated circuits based on the information in this document. NXP reserves the right to make changes without further notice to any products herein.

NXP makes no warranty, representation, or guarantee regarding the suitability of its products for any particular purpose, nor does NXP assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation consequential or incidental damages. "Typical" parameters that may be provided in NXP data sheets and/or specifications can and do vary in different applications, and actual performance may vary over time. All operating parameters, including "typicals," must be validated for each customer application by customer's technical experts. NXP does not convey any license under its patent rights nor the rights of others. NXP sells products pursuant to standard terms and conditions of sale, which can be found at the following address: [nxp.com/SalesTermsandConditions](http://nxp.com/SalesTermsandConditions).

While NXP has implemented advanced security features, all products may be subject to unidentified vulnerabilities. Customers are responsible for the design and operation of their applications and products to reduce the effect of these vulnerabilities on customer's applications and products, and NXP accepts no liability for any vulnerability that is discovered. Customers should implement appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP, the NXP logo, NXP SECURE CONNECTIONS FOR A SMARTER WORLD, COOLFLUX, EMBRACE, GREENCHIP, HITAG, I2C BUS, ICODE, JCOP, LIFE VIBES, MIFARE, MIFARE CLASSIC, MIFARE DESFire, MIFARE PLUS, MIFARE FLEX, MANTIS, MIFARE ULTRALIGHT, MIFARE4MOBILE, MIGLO, NTAG, ROADLINK, SMARTLX, SMARTMX, STARPLUG, TOPFET, TRENCHMOS, UCODE, Freescale, the Freescale logo, AltiVec, C-5, CodeTEST, CodeWarrior, ColdFire, ColdFire+, C-Ware, the Energy Efficient Solutions logo, Kinetis, Layerscape, MagniV, mobileGT, PEG, PowerQUICC, Processor Expert, QorIQ, QorIQ Qonverge, Ready Play, SafeAssure, the SafeAssure logo, StarCore, Symphony, VortiQa, Vybrid, Airfast, BeeKit, BeeStack, CoreNet, Flexis, MXC, Platform in a Package, QUICC Engine, SMARTMOS, Tower, TurboLink, and UMEMS are trademarks of NXP B.V. All other product or service names are the property of their respective owners. AMBA, Arm, Arm7, Arm7TDMI, Arm9, Arm11, Artisan, big.LITTLE, Cordio, CoreLink, CoreSight, Cortex, DesignStart, DynamIQ, Jazelle, Keil, Mali, Mbed, Mbed Enabled, NEON, POP, RealView, SecurCore, Socrates, Thumb, TrustZone, ULINK, ULINK2, ULINK-ME, ULINK-PLUS, ULINKpro,  $\mu$ Vision, Versatile are trademarks or registered trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere. The related technology may be protected by any or all of patents, copyrights, designs and trade secrets. All rights reserved. Oracle and Java are registered trademarks of Oracle and/or its affiliates. The Power Architecture and Power.org word marks and the Power and Power.org logos and related marks are trademarks and service marks licensed by Power.org.

© 2019 NXP B.V.

Document Number ARN  
Revision P9.0.0\_1.0.0-ga, 01/2019

